




PH100-SIUV-OD.3-D0

Photodiode detector for laser power measurement up to 16 mW.



PRODUCT FAMILY KEY FEATURES

LARGE APERTURES

10 mm Ø for the silicon sensors

3 VERSIONS

- Silicon 350 1080 nm, up to 750 mW
- Silicon-UV 210 1080 nm, up to 38 mW
- Germanium 800 1650 nm, up to 500 mW

CHOICE OF ATTENUATORS

- OD0.3: 50% transmission (for PH100-SI^{UV} only)
- OD1: 10% transmission
- OD2: 1% transmission

HIGH ACCURACY

The new PH100-SI-HA presents the lowest calibration uncertainty to date.

38.1Ø x 46.3D mm

PRECISE CALIBRATION

Wavelength selection in 1 nm steps

SMART INTERFACE

Containing all the calibration data

COMPATIBLE STAND

STAND-D-233

SPECIFICATIONS

| MEASUREMENT CAPABILITIES | |
|---|---|
| Maximum average power ¹ | 16 mW |
| Noise equivalent power ² | 20 pW |
| Spectral range | 210 - 1080 nm |
| Typical rise time | 0.2 s |
| Power calibration uncertainty ³ | ±18 % (210 - 229 nm) ±8.0 % (230 - 254 nm) ±6.5 % (255 - 399 nm) ±5.0 % (400 - 1009 nm) ±7.5 % (1010 - 1080 nm) |
| Peak sensitivity | 850 nm |
| Minimum repetition rate ⁴ | 155 kHz |
| 1. At 300 nm, with attenuator. See curves for maximum power at other wavelengths. 2. At 850 nm. Nominal value. Actual value depends on environmental electromagnetic interference and wavelength. 3. With attenuator. See user manual for calibration uncertainty without attenuator. | |

With attenuator. See user manual for calibration uncertainty without attenuator
See user manual for details.

DAMAGE THRESHOLDS

Dimensions

| Maximum average power density | 10 | 00 W/cm ² |
|-------------------------------|----|----------------------|
|-------------------------------|----|----------------------|

PHYSICAL CHARACTERISTICS

| Aperture diameter | 10 mm |
|-------------------|-------|
| Absorber | SiUV |

Weight 0.14 kg

Distance to sensor face





| ORDERING INFORMATION | |
|------------------------|--------|
| PH100-SiUV-OD.3-D0 | 202679 |
| PH100-SiUV-OD.3-INT-D0 | 202792 |
| PH100-SiUV-OD.3-IDR-D0 | 203238 |

Specifications are subject to change without notice. Refer to the user manual for complete specifications.

INTERESTED IN THIS PRODUCT?

GET A QUOTE

Find your local sales representative at gentec-eo.com/contact-us